September 2003

National Semiconductor

LM3702/LM3703
Microprocessor Supervisory Circuits with Low Line Output and Manual Reset

General Description

The LM3702/LM3703 series of microprocessor supervisory circuits provide the maximum flexibility for monitoring power supplies and battery controlled functions in systems without backup batteries. The LM3702/LM3703 series are available in a 9-bump micro SMD package.

Built-in features include the following:

Reset: Reset is asserted during power-up, power-down, and brownout conditions. $\overline{\text{RESET}}$ is guaranteed down to V_{CC} of 1.0V.

Manual Reset Input: An input that asserts reset when pulled low.

Low Line Output: This early power failure warning indicator goes low when the supply voltage drops to a value which is 2% higher than the reset threshold voltage.


Features

- Standard Reset Threshold voltage: 3.08V
- Custom Reset Threshold voltages: For other voltages between 2.2V and 5.0V in 10mV increments, contact National Semiconductor Corp.
- No external components required
- Manual-Reset input
- $\overline{\text{RESET}}$ (LM3702) or RESET (LM3703) outputs
- Precision supply voltage monitor
- Factory programmable Reset Timeout Delay
- Available in micro SMD package for minimum footprint
- ±0.5% Reset threshold accuracy at room temperature
- ±2% Reset threshold accuracy over temperature extremes
- Reset assertion down to 1V V_{CC} ($\overline{\text{RESET}}$ option only)
- 28 µA V_{CC} supply current

Applications

- Embedded Controllers and Processors
- Intelligent Instruments
- Automotive Systems
- Critical µP Power Monitoring

Typical Application




20011503

© 2003 National Semiconductor Corporation

Connection Diagram

Top View
(looking from the coating side)
micro SMD 9 Bump Package
BPA09




20011501

Pin Descriptions


Bump No.	Name	Function
A1	$\overline{MR}$	Manual-Reset input. When $\overline{MR}$ is less than V_{MRT} (Manual Reset Threshold) $\overline{RESET}$/RESET is engaged.
B1	V_{CC}	Power Supply input.
C1	$\overline{RESET}$	Reset Logic Output. Pulses low for t_{RP} (Reset Timeout Period) when triggered, and stays low whenever V_{CC} is below the reset threshold or when $\overline{MR}$ is below V_{MRT}. It remains low for t_{RP} after either V_{CC} rises above the reset threshold, or after $\overline{MR}$ input rises above V_{MRT} (LM3702 only).
	RESET	Reset Logic Output. RESET is the inverse of $\overline{RESET}$ (LM3703 only).
C3	$\overline{LLO}$	Low-Line Logic Output. Early Power-Fail warning output. Low when V_{CC} falls below V_{LLOT} (Low-Line Output Threshold). This output can be used to generate an NMI (Non-Maskable Interrupt) to provide an early warning of imminent power-failure.
B3	GND	Ground reference for all signals.
A2, A3, C2	NC	No Connect.
B2	NC	No Connect. Test input used at factory only. Leave floating.

Block Diagram



20011505

Ordering Information



20011504

*For other voltages between 2.2V and 5.0V, please contact National Semiconductor sales office.

LM3702/LM3703

Part Number	Output	Reset Timeout Period	Package Marking
LM3702XCBP-308	totem-pole	200ms	%%I2
LM3702XCBPX-308	totem-pole	200ms	%%I2
LM3703XCBP-308	totem-pole	200ms	%%I3
LM3703XCBPX-308	totem-pole	200ms	%%I3
LM3703XDBP-308	totem-pole	1600ms	%%124
LM3703XDBPX-308	totem-pole	1600ms	%%124
LM3702YABP-308	open-drain	1.4ms	%%131
LM3702ABPX-308	open-drain	1.4ms	%%131
LM3702YDBP-220	open-drain	1600ms	%%125
LM3702YDBPX-220	open-drain	1600ms	%%125

%% is the datecode and will vary with time.

Table Of Functions

Part Number	Active Low Reset	Active High Reset	Output (X = totem-pole) (Y = open-drain)	Reset Timeout Period	Manual Reset	Low Line Output
LM3702	x		X, Y*	Customized	x	x
LM3703		x	X	Customized	x	x

* = available upon request. Contact National

Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

Supply Voltage (V_{CC})	−0.3V to 6.0V
All Other Inputs	−0.3V to V_{CC} + 0.3V
ESD Ratings (Note 2)	
Human Body Model	1.5kV
Machine Model	150V
Power Dissipation	(Note 3)

Operating Ratings (Note 1)

Temperature Range	$-40^{\circ}C \le T_J \le 85^{\circ}C$

LM3702/LM3703 Series Electrical Characteristics

Limits in the standard typeface are for T_J = 25˚C and limits in **boldface type** apply over full operating range. Unless otherwise specified: V_{CC} = +2.2V to 5.5V.

Symbol	Parameter	Conditions	Min	Typ	Max	Units
POWER SUPPLY						
V_{CC}	Operating Voltage Range: V_{CC}	LM3702	**1.0**		**5.5**	V
		LM3703	**1.2**		**5.5**	
I_{CC}	V_{CC} Supply Current	All inputs = V_{CC}; all outputs floating		28	**50**	µA
RESET THRESHOLD						
V_{RST}	Reset Threshold	V_{CC} falling	−0.5 **−2**	V_{RST}	+0.5 **+2**	%
		V_{CC} falling: T_A = 0˚C to 70˚C	**−1.5**		**+1.5**	
V_{RSTH}	Reset Threshold Hysteresis			0.0032•V_{RST}		mV
t_{RP}	Reset Timeout Period	Reset Timeout Period = A	**1**	1.4	**2**	ms
		Reset Timeout Period = B	**20**	28	**40**	
		Reset Timeout Period = C	**140**	200	**280**	
		Reset Timeout Period = D	**1120**	1600	**2240**	
t_{RD}	V_{CC} to Reset Delay	V_{CC} falling at 1mV/µs		20		µs
RESET (LM3703)						
V_{OL}	RESET	V_{CC} > 2.25V, I_{SINK} = 900µA			**0.3**	V
		V_{CC} > 2.7V, I_{SINK} = 1.2mA			**0.3**	
		V_{CC} > 4.5V, I_{SINK} = 3.2mA			**0.4**	
V_{OH}	RESET	V_{CC} > 1.2V, I_{SOURCE} = 50µA	**0.8 V_{CC}**			V
		V_{CC} > 1.8V, I_{SOURCE} = 150µA	**0.8 V_{CC}**			
		V_{CC} > 2.25V, I_{SOURCE} = 300µA	**0.8 V_{CC}**			
		V_{CC} > 2.7V, I_{SOURCE} = 500µA	**0.8 V_{CC}**			
		V_{CC} > 4.5V, I_{SOURCE} = 800µA	**V_{CC} − 1.5V**			
I_{LKG}	Output Leakage Current	V_{RESET} = 5.5V			**1.0**	µA
$\overline{\text{RESET}}$ (LM3702)						
V_{OL}	$\overline{\text{RESET}}$	V_{CC} > 1.0V, I_{SINK} = 50µA			**0.3**	V
		V_{CC} > 1.2V, I_{SINK} = 100µA			**0.3**	
		V_{CC} > 2.25V, I_{SINK} = 900µA			**0.3**	
		V_{CC} > 2.7V, I_{SINK} = 1.2mA			**0.3**	
		V_{CC} > 4.5V, I_{SINK} = 3.2mA			**0.4**	
V_{OH}	$\overline{\text{RESET}}$	V_{CC} > 2.25V, I_{SOURCE} = 300µA	**0.8 V_{CC}**			
		V_{CC} > 2.7V, I_{SOURCE} = 500µA	**0.8 V_{CC}**			
		V_{CC} > 4.5V, I_{SOURCE} = 800µA	**V_{CC} − 1.5V**			

LM3702/LM3703 Series Electrical Characteristics (Continued)

Limits in the standard typeface are for T_J = 25˚C and limits in **boldface type** apply over full operating range. Unless otherwise specified: V_{CC} = +2.2V to 5.5V.

Symbol	Parameter	Conditions	Min	Typ	Max	Units
$\overline{MR}$						
V_{MRT}	$\overline{MR}$ Input Threshold	$\overline{MR}$, Low			**0.8**	V
		$\overline{MR}$, High	**2.0**			
V_{MRTH}	$\overline{MR}$ Threshold Hysteresis	$\overline{MR}$ falling: V_{CC} = $V_{RST\ MAX}$ to 5.5V		0.0032•V_{RST}		mV
R_{MR}	$\overline{MR}$ Pull-up Resistance		**35**	56	**75**	kΩ
t_{MD}	$\overline{MR}$ to Reset Delay			12		µS
t_{MR}	$\overline{MR}$ Pulse Width		**25**			µS
$\overline{LLO}$						
V_{OL}	$\overline{LLO}$ Output Voltage	V_{CC} > 2.25V, I_{SINK} = 900µA			**0.3**	V
		V_{CC} > 2.7V, I_{SINK} = 1.2mA			**0.3**	
		V_{CC} > 4.5V, I_{SINK} = 3.2mA			**0.4**	
V_{OH}		V_{CC} > 2.25V, I_{SOURCE} = 300µA	**0.8 V_{CC}**			
		V_{CC} > 2.7V, I_{SOURCE} = 500µA	**0.8 V_{CC}**			
		V_{CC} > 4.5V, I_{SOURCE} = 800µA	**V_{CC} – 1.5V**			
$\overline{LLO}$ OUTPUT						
V_{LLOT}	$\overline{LLO}$ Output Threshold ($V_{\overline{LLO}}$ – V_{RST}, V_{CC} falling)		**1.01•V_{RST}**	1.02•V_{RST}	**1.03•V_{RST}**	V
V_{LLOTH}	Low-Line Comparator Hysteresis			0.0032•V_{RST}		mV
t_{CD}	Low-Line Comparator Delay	V_{CC} falling at 1mV/µs		20		µs

Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. **Operating Ratings** indicate conditions for which the device is intended to be functional, but do not guarantee specific performance limits. For guaranteed specifications and test conditions, see the Electrical Characteristics. The guaranteed specifications apply only for the test conditions listed. Some performance characteristics may degrade when the device is not operated under the listed conditions.

Note 2: The Human Body model is a 100 pF capacitor discharged through a 1.5 kΩ resistor into each pin. The machine model is a 200pF capacitor discharged directly into each pin.


Note 3: The maximum allowable power dissipation is a function of the maximum junction temperature, T_J(MAX), the junction-to-ambient thermal resistance, θ_{J-A}, and the ambient temperature, T_A. The maximum allowable power dissipation at any ambient temperture is calculated using:

$$P(MAX) = \frac{T_J(MAX) - T_A}{\theta_{J-A}}$$

Where the value of θ_{J-A} for the micro SMD package is 220˚C/W.


Typical Performance Characteristics

Supply Current vs Supply Voltage




20011515

3.3V Supply Current vs Temperature




20011511

Normalized Reset Threshold Voltage vs Temperature




20011512

Reset Timeout Period vs V_{CC}




20011532

Reset Timeout Period vs Temperature



20011510


Max. Transient Duration vs Reset Comparator Overdrive (V_{CC} = 3.3V)



20011516

Typical Performance Characteristics (Continued)

Low-Line Comparator Propagation Delay vs Temperature



20011514

Circuit Information

RESET OUTPUT

The Reset input of a µP initializes the device into a known state. The LM3702/LM3703 microprocessor supervisory circuits assert a forced reset output to prevent code execution errors during power-up, power-down, and brownout conditions.

$\overline{\text{RESET}}$ is guaranteed valid for V_{CC} > 1V. Once V_{CC} exceeds the reset threshold, an internal timer maintains the output for the reset timeout period. After this interval, reset goes high. The LM3702 offers an active-low $\overline{\text{RESET}}$; The LM3703 offers an active-high RESET.

Any time V_{CC} drops below the reset threshold (such as during a brownout), the reset activates. When V_{CC} again rises above the reset threshold, the internal timer starts. Reset holds until V_{CC} exceeds the reset threshold for longer than the reset timeout period. After this time, reset releases.

The Manual Reset input ($\overline{\text{MR}}$) will initiate a forced reset also. See the *Manual Reset Input* section.

RESET THRESHOLD

The LM3702/LM3703 family is available with a reset voltage of 3.08V. Other reset thresholds in the 2.20V to 5.0V range, in steps of 10 mV, are available; contact National Semiconductor for details.

MANUAL RESET INPUT ($\overline{\text{MR}}$)

Many µP-based products require a manual reset capability, allowing the operator to initiate a reset. The $\overline{\text{MR}}$ input is fully debounced and provides an internal 56 kΩ pull-up. When the $\overline{\text{MR}}$ input is pulled below V_{MRT} (1.225V) for more than 25 µs, reset is asserted after a typical delay of 12 µs. Reset remains active as long as $\overline{\text{MR}}$ is held low, and releases after the reset timeout period expires after $\overline{\text{MR}}$ rises above V_{MRT}. Use $\overline{\text{MR}}$ with digital logic to assert or to daisy chain supervisory circuits. It may be used as another low-line comparator by adding a buffer.

LOW-LINE OUTPUT ($\overline{\text{LLO}}$)

The low-line output comparator is typically used to provide a non-maskable interrupt to a µP when V_{CC} begins falling. $\overline{\text{LLO}}$ monitors V_{CC} and goes low when V_{CC} falls below V_{LLOT} (typically 1.02 • V_{RST}) with hysteresis of 0.0032 • V_{RST}.

SPECIAL PRECAUTIONS FOR THE MICRO SMD PACKAGE

As with most integrated circuits, the LM3702 and LM3703 are sensitive to exposure from visible and infrared (IR) light radiation. Unlike a plastic encapsulated IC, the micro SMD package has very limited shielding from light, and some sensitivity to light reflected from the surface of the PC board or long wavelength IR entering the die from the side may be experienced. This light could have an unpredictable affect on the electrical performance of the IC. Care should be taken to shield the device from direct exposure to bright visible or IR light during operation.

MICRO SMD MOUNTING

The micro SMD package requires specific mounting techniques which are detailed in National Semiconductor Application Note AN-1112. Referring to the section ***Surface Mount Technology (SMT) Assembly Considerations***, it should be noted that the pad style which must be used with the 9-pin package is the NSMD (non-solder mask defined) type.

For best results during assembly, alignment ordinals on the PC board may be used to facilitate placement of the micro SMD device.

Timing Diagrams




FIGURE 1. LM3702 Reset Time with $\overline{MR}$




FIGURE 2. $\overline{LLO}$ Output

Typical Application Circuits




FIGURE 3. LM3703 Power-On Delay

Typical Application Circuits (Continued)




FIGURE 4. Regulator/Switch with Long-Term Overvoltage Lockout Prevents Overdissipation in Linear Regulator





FIGURE 5. Switch Debouncer

Physical Dimensions inches (millimeters)

unless otherwise noted



NOTES: UNLESS OTHERWISE SPECIFIED

1. EPOXY COATING
2. 63Sn/37Pb EUTECTIC BUMP
3. RECOMMEND NON-SOLDER MASK DEFINED LANDING PAD.
4. PIN 1 IS ESTABLISHED BY LOWER LEFT CORNER WITH RESPECT TO TEXT ORIENTATION. REMAINING PINS ARE NUMBERED COUNTER CLOCKWISE.
5. XXX IN DRAWING NUMBER REPRESENTS PACKAGE SIZE VARIATION WHERE X1 IS PACKAGE WIDTH, X2 IS PACKAGE LENGTH AND X3 IS PACKAGE HEIGHT.
6. NO JEDEC REGISTRATION AS OF AUG.1999.

9 bump micro SMD Package
NS Package Number BPA09FFB
The dimensions of X1, X2 and X3 are given below
X1 = 1.412mm
X2 = 1.412mm
X3 = 0.850mm

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

National Semiconductor
Americas Customer
Support Center
Email: new.feedback@nsc.com
Tel: 1-800-272-9959

www.national.com

National Semiconductor
Europe Customer Support Center
Fax: +49 (0) 180-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171
Français Tel: +33 (0) 1 41 91 8790

National Semiconductor
Asia Pacific Customer
Support Center
Email: ap.support@nsc.com

National Semiconductor
Japan Customer Support Center
Fax: 81-3-5639-7507
Email: jpn.feedback@nsc.com
Tel: 81-3-5639-7560

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.